### VM901-1W Wi-Fi 1080p

Pan & Tilt Video Monitor





# vtech Quick start guide

### Congratulations

on purchasing your new VTech product. Before using this HD video monitor, please read Important safety instructions

hat does HD Video Monitor do?


VTech Wi-Fi HD Video Monitor allows you to stay close to your baby when you are on the move or away.

This monitor is Wi-Fi enabled, which uses your home wireless network to stream live video and audio through the HD baby unit and 5-inch colour screen parent unit. It allows you to maintain a constant connection to your baby.

You can also monitor from your smartphone and mobile tablet.

VTech Wi-Fi HD Video Monitor uses MyVTech Baby Pro app to let you instantly see and hear what's happening with your baby from anywhere in the world.

The app can be downloaded from the App Store or the Google Play™ Store, directly from your smartphone or mobile tablet.





OS is a trademark or registered trademark of Cisco in the U.S. and other countries and is used under license. App Store is a trademark of Apple Inc., registered in the U.S. and other countries. Android<sup>TM</sup> and Google Play<sup>TM</sup> are trademarks of Google Inc.

	HIN 2412 - 2412 ALM 2742 MLC Wm00L) WL.0 : The transmitter: 0.1W (IOmW)
Channels 13	J3
	5" Colour LCD (IPS 1280x720 pixels)
	Actual operating range may vary according to environmental conditions at the time of use.
	<ul> <li>I. Parent unit power adaptor:</li> <li>Output: 5V DC 2A</li> <li>S. To DC 2A</li> <li>S. Parent unit: 3.7V Lithium-ion Polymer battery</li> </ul>
	3. Baby unit power adaptor: Output: 5V DC IA

# **TECHNICAL SPECIFICATIONS**

### **IMPORTANT SAFETY INSTRUCTIONS**

The applied nameplate is located at the bottom of the When using your equipment, basic safety precaution lways be follo wed to reduce the risk of fire,

electric shock and injury, including the following: 1. Follow all warnings and instructions marked on the

- Adult setup is reauired
- 3. CAUTION: Do not install the baby unit at a height ove 2 metres
- 4. This product is intended as an aid. It is not a substitute for be used as such.
- This product is not intended for use as a medical monitor Do not use this product near water, for example, near to a bath, sink, swimming pool or shower.
- CAUTION: Use only the battery provided. There may be a risk of explosion if a wrong type of battery is used for the parent unit. The battery cannot be
- subjected to high or low extreme temperature and ow air pressure at high altitude during use, storage o ansportation. Disposal of battery in fire or a hot over mechanically crushing or cutting the battery can result in an explosion. Leaving the battery in an extremely an explosion or the leakage of flammable liquid of aas. Battery subjected to extremely low air pressure ay result in an explosion or the leakage of flamm iquid or gas. Dispose of used batteries according to the nation in instructions.
- . Use only the power adaptors included with this roduct. Incorrect power adaptors polarity or voltage an seriously damage the product.

Power adaptor information: Parent unit output: 5V DC 2A

VTech Telecommunications Ltd Model: VT07EUK05200 Baby unit output: 5V DC 1A VTech Telecommunications Ltd

lodel: VT05EUK05100

- A C Rechargeable battery information 3.7V 5000mAh, 18.5Wh Lithium-ion battery; uhai Great Power Energy Co., Ltd.
- Model: GSP806090-5Ah-3.7V-1S1P 9. The power adaptors are intended to be correctly oriented in a vertical or floor mount position. The prongs are not designed to hold the plug in place if it plugged into a ceiling, under-the-table or cabinet
- 10. For pluggable equipment, the socket-outlet should e installed near the equipment and should be easily accessible.
- 11. Unplug this product from the wall outlet before cleaning. o not use liquid or aerosol cleaners. Use a damp cloth
- 12. Do not modify the power adaptors or replace with ther adaptors, as this causes a hazardous situatio 13. Do not allow anything to rest on the power cords. Do
- ot install this product where the cords may be walked on or crimped.
- 14. This product should be operated only from the type of power source indicated on the marking label. If you are not sure of the type of power supply in your home consult your dealer or electricity supply provider. Do not overload wall outlets or use an extension cord 16. Do not place this product on an unstable table, shelf, and or other unstable surfaces.

This product should not be placed in any area where proper ventilation is not provided. Slots and opening in the back or bottom of this product are provided for ventilation. To protect them from overheating, these openings must not be blocked by placing the product on a soft surface such as a bed, sofa or rug. This product should never be placed near or over a radiator or heat 18. Never push objects of any kind into this product

- voltage points or create a short circuit. Never spill liquid of any kind on the product
- To reduce the risk of electric shock, do not disassemble this product, but take it to an authorised service facility. Disassembling o removing parts of the product other than via the battery door may expose you to dangero voltages or other risks. Incorrect reassembling can cause electric shock when the product is subsequently used. . You should test the sound reception every time you

turn on the units or move one of the components. Periodically examine all components for damage. There is a very low risk of privacy loss when using

- ones, etc. To protect your privacy, make sure the product has never been used before purchase, reset the baby monitor periodically by powering off and then powering on the units, and power off the baby monitor if you are not intending to use it for some time.
- by babies or small children. Keep these parts out of reach of children.
- not play with the product.
- (including children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for their safety SAVE THESE INSTRUCTIONS

Cautions

- 0°C and 40°C
- Do not expose the product to extreme cold, heat or direct sunlight. Do not put the product close to a
- Mishandling batteries can cause burn, fire or
- explosion hazards
- Warning-Strangulation Hazard-Children have STRANGLED in cords. Keep this cord out of the reach of children (more than 0.9m away). Do not remove warning label on the adaptor

Never place the baby unit(s) inside the baby's cot or playpen. Never cover the baby unit(s) or parent unit with anything such as a towel or a blanket.

Other electronic products may cause interference with your baby monitor. Try installing your baby monitor as far away from these electronic devices as possible: wireless routers, radios, cellular telephones, intercoms, room monitors, television personal computers, kitchen appliances and

# PROTECT YOUR PRIVACY AND ONLINE SECURITY

VTech cares about your privacy and peace of mind. That's why we've put together a list of industry-recommended best practices to help keep your wireless connection private and your devices protected when online. We recommend you carefully review and consider complying with the following tips

Ensure your wireless connection is secure.

• Before installing a device, ensure your router's wireless signal is encrypted by selecting the "WPA2-PSK with AES" setting in your router's wireless security menu.

Change default settings.

- Change your wireless router's default wireless network name (SSID) to something unique. Change default passwords to unique, strong passwords. A strong password:
- Is at least 10 characters long.
- Is complex.

entire network.

- Does not contain dictionary words or personal information.
- Contains a mix of uppercase letters, lowercase letters, special characters and numbers. Keep your devices up to date

Download security patches from manufacturers as soon as they become available. This

- will ensure you always have the latest security updates. • If the feature is available, enable automatic updates for future releases.
- Disable Universal Plug and Play (UPnP) on your router.
- UPnP enabled on a router can limit the effectiveness of your firewall by allowing other network devices to open inbound ports without any intervention or approval from you. A virus or other malware program could use this function to compromise security for the

For more information on wireless connections and protecting your data, please review the following resources from industry experts:

1. Federal Communications Commission: Wireless Connections and Bluetooth Security Tips

- www.fcc.gov/consumers/guides/how-protect-yourself-online.
- 2. U.S. Department of Homeland Security: Before You Connect a New Computer to the Internet – <u>www.us-cert.gov/ncas/tips/ST15-003</u>.
- 3. Federal Trade Commission: Using IP Cameras Safely -
- https://www.consumer.ftc.gov/articles/0382-using-ip-cameras-safely.
- 4. Wi-Fi Alliance: Discover Wi-Fi Security http://www.wi-fi.org/discover-wi-fi/security.

certain electronic devices, such as baby monito

- The small parts of this monitor can be swallowed
- 4. Children should be supervised to ensure that they do
- 25. The product is not intended for use by persons

- 1. Use and store the product at a temperature between

- 4. Batteries should not be exposed to excessive heat such as bright sunshine or fire.

cordless telephones.


### NOTES

- product.
- outlet.

Connect the power adaptors in a vertical or floor mount position only. The adaptor prongs are not designed to hold the weight of the parent unit and the baby unit, so do not connect them to any ceiling under-the-table, or cabinet outlets. Otherwise, the adaptors may not properly connect to the outlets Make sure the parent unit, the baby unit and the power adaptor cords are out of reach of children.

# WHAT'S IN THE BOX

Your HD video monitor package contains the following items. Save your sales receipt and original packaging in the event warranty service is necessary.



Requirements		
For mobile access:		
MyVTech Baby Pro MOBILE APP		
Network	Wi-Fi	
Wi-Fi router	2.4GHz 802.11 b/g/n	_

Internet connection	1.5 Mbps @ 720p or 2.5 Mbps @1080p upload bandwidth per baby unit
---------------------	---

# Connect, charge and power on the baby monitor

### Connect the baby monitor

The rechargeable battery in the parent unit is built-in. Use only the power adaptors supplied with this

Make sure the parent unit and the baby unit are not connected to an electronically controlled electric

### Connect and power on the baby unit

1. Connect the power adaptor to the baby unit and a power supply.

2. Slide the  $\bigcirc$  **ON/OFF** switch to the left to power on your baby unit.


### 🖹 Notes


When powering up, the baby unit's status LED turns on. It will turn off after a while and remains off. The status LED is set to off by default. If you want to keep the LED on, press **MENU**, then go to







Camera lens and surface may get warm during normal operation.











### Parent unit overview

🛲 LED light

### Microphone

### Camera lens

- LED indicators Flash orange and green alternately when the baby unit is in pairing
- Orange is steady on when the baby unit is not connecting to the Internet and is idle.
- Green is steady on when the baby unit is connecting to the Internet and is idle
- Flash orange slowly when the baby unit is not connecting to the Internet and is streaming with the parent unit.
- Flash green slowly when the baby unit is connecting to the Internet and streaming with the parent unit or mobile app.
- Flash orange and green quickly and alternately when the baby unit is updating its firmware.

Allow you to see clearly in a dark

Connect to router with Wi-Fi.

provided are already paired.

### is set to off. • On when the parent unit is talking to the baby unit

low and needs charging.

from AC power.

LINK LED light

baby unit.

🖏 LED light

- TALK LED light • On when the parent unit is talking to the baby unit

### Options Menu Melodies and soothing sounds Select play all melodies, or play one of the five melodies and five soothing sounds. • You can also set the timer to stop playing after 15, 30 or 60 minutes, or play non-stop. Alerts - Sound, motion and temperature Turn on/off sound detection motion detection, and t**emperature** alerts. Select the sound and motion sensitivity level.

 Select maximum and minimum temperature for alert range. Set the temperature format to Fahrenheit (°F) or Celsius (°C).

	•	Adjust pare brightness
	•	Adjust <b>Low</b> volume leve
	•	Adjust No


- volume level.
- Baby unit settings

### Turn on/off Night Vision


	<ul> <li>Turn on/off</li> </ul>		
	• Turn on/off I		
	<ul> <li>Adjust baby volume.</li> </ul>		
General settings			


### General settings

- O
- Connect to home Wi-Fi network. Connect mobile phone. • **Reset settings** to factory default. • Software Update.




The screen displays 🛄 and The battery has very little Charge without interruption (about








To keep the battery charged, connect

it to AC power when in use.









# Speaker

- Temperature sensor
- 10 Power jack

### Threaded socket


12 Pair/reset button


# The parent unit and baby unit

# **PARENT UNIT ICONS**









	<u> </u>
(8)	
<u>Г</u>	
Ш	
A	
	$\sim$

Charge the battery before use

short time only.

🖹 Notes

solid 🛄.

Raise the parent unit

antenna for better reception

The parent unit runs on an internal rechargeable battery

keep the parent unit connected to AC power. With the

battery alone, the parent unit can cordlessly run for a

Before using the baby monitor for the first time, charge

the parent unit battery for 12 hours. When the parent unit

It takes longer to charge when the parent unit is turned on.

• The standby time varies depending on your actual use.

The battery icon becomes The battery is fully

turn it on or press and hold to turn it off.

battery is fully charged, the battery icon becomes solid **(** 

The battery icon indicates the battery status (see the following table).

. The **—** light flashes. charge and may be used for only a short time.

charged.

or AC power. To continuously monitor your baby,

Light sensor

	6	
	8	
_	19	
	346	
	B	

- On when the parent unit is connected to AC power, or the battery is charging. • Flashes when the parent unit battery is • Off when the parent unit is disconnected
- On when the parent unit is linked to the Flashes when the link to the baby unit is On when the parent unit speaker volume

### LCD display

- Microphone
- LCD ON/OFF
- POWER
- **♫** Lullaby • Press to enter the lullaby menu.
- 10 TALK
- Press and hold to talk to the baby unit. • While in a submenu, press to exit.
- Arrow kevs
- <, **A**, **>** or **V** • Press to move the selection box leftward, upward, rightward or downward.
- While viewing image from the baby unit, <u>press and hold</u> to pan the baby unit leftward, upward, rightward or downward.
- While viewing zoomed image, press and hold to move the zoomed image leftward, upward, rightward or downward.
- MENU/SELECT
- Press to enter the menu. While in a menu, press to select an item,
- or save a setting.
- 🕀 Zoom in
- igoa Zoom out
- VOL/ VOL +

13

- Antenna
- RESET 17
- Force reboot the parent unit.
- 18 Speaker
- Power iac Stand


# How the system works

 $\lesssim T_{IP}$  For better security and more stable connectivity, this baby monitor requires connecting to a Wi-Fi network and operating in Router mode connection.

### Direct mode

Your baby monitor parent unit and baby unit connect to each other in Direct mode by default, which allows you to immediately stream video out of the box.

It is NOT recommended to continue using Direct Mode connection after initial installation.



### Router mode


You are required to set up your monitor in **Router mode** to enjoy live video streaming via your parent unit with an enhanced connection. Router mode is the recommended mode for stable connectivity.

**Router mode** uses your home Wi-Fi network to connect your video monitor. It supports live video streaming through the parent unit and smartphone app.

If you want to stream live video remotely with your mobile device, download and install the **MyVTech Baby Pro** mobile app. With the mobile

app, your Wi-Fi router (not included) provides Internet connectivity to your HD video monitor system. It serves as a communicating channel between your baby unit and mobile device, allowing you to monitor and/or control your baby unit wherever you are. For more details, see **Download** app for mobile access section in this quick start quide.

### 🖹 Note





Scan to learn more on improving connectivity.

- rent unit screen
- v Battery Alert Tone
- o Link Alert Tone
- Turn on/off dim mode.
  - baby unit's status LED. unit's speaker

# Status icons

Parent unit and baby unit are 100 connected to each other directly Red bars indicate no connection

### Router mode

- The parent unit and baby unit connect via the Wi-Fi network. The red icon on the baby unit or parent unit, indicates no connectio between the respective unit(s) and the
- Night vision is turned on.
- Motion alert is turned on.
- Sound detection alert is turned on
- Melodies and soothing sounds are turned on.
- 6-level sound indicator indicates low sound level
  - ected by the baby unit. indicates moderate sound level
  - cted by the baby unit.
  - indicates high sound level detected by the baby unit.
- Parent unit speaker is muted.

Temperature alert is turned on.

Download the free **MyVTech Baby Pro** mobile app and install it to a mobile device, then use your mobile device and the mobile app to monitor your areas remotely.

### 🖹 NOTE

- Make sure your video monitor is connected with your Wi-Fi network
- 1. Press **MENU/SELECT** when the parent unit is idle.
- 2. Go to 🔅 > Connect Mobile Phone.
- 3. Scan the QR code in the parent unit to download the app into your mobile device.
- 4. Follow the instructions in the mobile app to set up and pair your baby unit to the mobile app.

Alternatively, you can download the mobile app from the App Store or Google Play store.

### Install MyVTech Baby Pro mobile app

- 1. Browse the App Store 🙆 or the Google Play store 📡
- 2. Search for the mobile app with the keyword "myvtech baby pro".
- 3. Download and install the **MyVTech Baby Pro** mobile app to your mobile device. 回流回

### OR

Scan the QR codes on the right to get the app.

### NOTE

· Make sure your mobile device meets the minimum requirement for the mobile app.

### Minimum requirement

### The mobile app is compatible with:

- Android<sup>™</sup> 6.0 or later; and
- iOS 12 or later.

After installing the mobile app, follow the instructions in the mobile app and parent unit to set up and pair your baby unit.

### In your mobile device:

- 1. Tap 🐸 to run the mobile app in your mobile device, and then create a user account.
- 2. We recommend that you use common webmail services, such as Google Gmail for registration of your user account. Check your email (and Spam folder), and activate your new camera account via the email link, then sign in to your account.
- 3. Follow the instructions in the mobile app to pair the camera. Tap 🚍 then Add Camera in the mobile app to get started.



尜Tip

You may experience reduced signal

baby unit are far apart, or there are

obstructing factors, such as internal

walls, between them. You have to

set up Router mode to connect the

parent unit and baby unit.

units via your home Wi-Fi network to


improve the connection between you

wiFi

strength if your parent unit and








# Test the sound level and position the HD video monitor

This HD video monitor is intended as an aid. It is not a substitute for proper adult supervision, and should not be used as such.

### Testing the sound level of the HD video monitor

(1)For hearing protection, make sure the parent unit is more than 1 metre away from the baby unit. If you hear any feedback noise from the parent unit, move the parent unit further until the noise stops. You can also press - VOL on the parent unit to lower or mute the noise.

Increase the parent unit speaker volume if you cannot hear the sounds transmitted from the baby unit.





### Positioning the HD video monitor

Keep the baby unit out of the reach of your baby. Never place or mount the baby unit inside the baby's cot or


1. Place the baby unit more than 1 metre away from your baby.

2. Adjust the angle of the baby unit to aim at your baby. Refer to the online help on how to use the Pan/tilt and Zoom functions of the baby unit.






• Turn down the volume of your parent unit.



4. To avoid interference from other electronic devices, place your baby monitor at least 1 metre away from devices such as wireless routers, microwaves, mobile phones and computers.



# Seneral product care

- To keep this product working well and looking good, follow these guidelines:
- · Avoid placing it near heating appliances and devices that generate electrical noise (for example, motors or fluorescent lamps).
- DO NOT expose it to direct sunlight or moisture.
- Avoid dropping the product or treating it roughly.
- Clean with a soft damp cloth.
- DO NOT immerse the parent unit and the baby unit in water and do not clean them under running
- DO NOT use cleaning spray or liquid cleaners.
- Make sure the parent unit and the baby unit are dry before you connect them to the mains again.

# **STORAGE**

When you are not going to use the HD video monitor for some time, store the parent unit, the baby unit and the adaptors in a cool, dry place.

### ADULT SUPERVISION

- This baby monitor should be for use by adults only.
- Do not place the baby unit inside the cot or playpen.
- To ensure your children's safety, do not allow them to touch or play with the baby monitor and its accessories. THIS IS NOT A TOY.

# CUSTOMER SERVICE AND PRODUCT WARRANTY



# **PRODUCT WARRANTY**

- Thank you for choosing this quality product from VTech We hope it will bring many hours of entertainment, imaginative play and learning. The product detailed above is covered by a one year warranty from the date of purcha
- against any defects in materials or workmanship. 2. The product may be returned to the place of purchase. Alternatively the product can be
- returned to VTech Electronics Europe plc (see address below), with proof of purchase, without proof of purchase no replacement will be provided.
- VTech Electronics Europe plc will examine the product and if it is found to be defective due to faulty materials or workmanship, will replace the product at their discretion . If the product covered by this warranty is damaged due to misuse, modification c
- unauthorised repair, or because of faulty batteries, battery discharge or incorrect electrical connections, then this warranty becomes void.
- . This warranty is personal to the original purchaser and is not transferable.
- . Breakages to the LCD screen are not covered by the warranty. Returns to VTech Electronics Europe plc should include a cheque or postal order for
- £1.50 towards the cost of return postage and packaging.
- 3. Products returned to VTech Electronics Europe plc, should be addressed as follows and nacked carefully to avoid damage in transit (Please do not include batteries or adaptor Please include details of the fault together with your name and address.
- 9. To keep an online record of your warranty, please register your product online at www vtech.co.uk/warranty
- Vtech Electronics EU PLC, c/o XPO Logistics, Warehouse 350, Cat & Fiddle Lane, West
- lallam, DE7 6HE
- HIS WARRANTY IS OFFERED AS AN EXTRA BENEFIT AND DOES NOT AFFEC ONSUMERS' STATUTORY RIGHTS
- This warranty is valid for the UK and Eire only. For products purchased outside the UK and Eire, please contact your local distributor or place of purchase.

### IMPORTANT

Please retain this booklet with your sales receipt as proof of the date of purchase.

### **Customer Service**

Please visit www.vtechphones.eu to contact our Customer Service Department.



If you plan to install your baby unit in a designated location, and use your home Wi-Fi network to connect your video monitor, you need to test which of your selected monitoring areas within the house have good Wi-Fi signal strength. After you have powered on your parent unit, you can use your parent unit's Wi-Fi signal strength indicator to assist in checking. Once you have identified the suitable location, you can install your baby unit. Adjust the distance between your baby unit and the Wi-Fi router if needed.

factors, such as the effect distance and internal walls have on signal strength, you may experience reduced Wi-Fi signal. To improve the Wi-Fi signal strength, adjust the distance or direction of your parent unit. Check with your parent unit again.

This product is intended for use within Europe and UK. This equipment complies with the essential requirements to EU's Radio Equipment Directive (2014/53/EU) and the UK's Radio Regulations 2017 on radio systems and telecommunication equipment VTech Telecommunications Ltd. hereby declares that this Video Monitor VM901-1W is in compliance with the essential requirements and other relevant provisions of EU's Radio Equipment Directive (2014/53/EU) and UK's Radio Equipment Regulations 2017. The Declaration of Conformity for the VM901-1W is available from

www.vtechphones.eu



(2006/66/EC)

Help protect the environment by disposing of your product or batteries responsibly.

Android <sup>TM</sup> and Google Play <sup>TM</sup> are trademarks of Google Inc. App Store is a trademark of Apple Inc., registered in the U.S. and other countries. iOS is a trademark or registered trademark of Cisco in the U.S. and other countries and is used under license.

Manufacturer: VTech Telecommunications Ltd. Importer: VTech Electronics Europe Plc

# AUTO SOFTWARE AND FIRMWARE UPDATE

To ensure that your HD video monitor is always at its best performance, the Parent Unit will prompt a message and ask you to update its software and the Baby Unit's firmware when there are new versions available. Select "Now" to reboot the system, or switch off and on the Parent Unit later to reboot the system into the latest software.

To check if your device is running on the latest software, or to update your device


### Connect your HD video monitor with home Wi-Fi network

You must connect your video monitor to your secured home Wi-Fi network in order to receive the latest software and firmware updates. To set the Wi-Fi up, go to:

Make sure the Baby Unit is on when you set up the Wi-Fi network.

# TEST THE LOCATION FOR THE BABY UNIT

Depending on surroundings and obstructing



# Q<sub>s</sub> Frequently asked questions

Below are the questions most frequently asked about the baby monitor

Why does the baby monitor not respond normally?	<ul> <li>Try the following (in the order listed) for common cure:</li> <li>1. Disconnect the power to the baby unit and the parent unit.</li> <li>2. Wait a few seconds before connecting power back to the baby unit and the parent unit.</li> <li>3. Turn on the baby unit and the parent unit.</li> <li>4. Wait for the parent unit to synchronise with the baby unit. Allow up to one minute for this to take place.</li> </ul>
Why doesn't the baby unit and parent unit power-on light illuminate when the units are switched on?	Perhaps the parent unit is not connected to the power. Insert the adaptor plug into the parent unit and insert the adaptor in a wall socket. Then, press <b>POWER</b> to switch on the parent unit to establish connection with the baby unit.
	Perhaps the baby unit is not connected to the power. Insert the adaptor plug into the baby unit and insert the adaptor in a wall socket. Then, slide the $\bigcirc ON/OFF$ switch to <b>ON</b> to switch on the baby unit and to establish connection with the parent unit.
Why doesn't my parent	Make sure the power is not controlled by a electronic wall switch.
unit charge while connected to AC power?	The battery may de degraded through extended use or defective. See <b>Warranty</b> for repair/replacement.
Why is my screen in black and white?	The screen is in black and white during night-time or in a dark room when the night vision feature is activated. This is normal.
Why do I get glare or blurry display on my screen when viewing my baby at night?	During night-time or in a dark room, the surroundings and other interfering factors, like lighting, objects, colours and backgrounds may affect the image quality on your parent unit screen. Adjust the baby unit angle or place the baby unit at a higher level to prevent glare and a blurry display.
Why does the baby monitor produce a feedback noise?	<ul> <li>The parent unit and baby unit may be too close to each other.</li> <li>Move the parent unit away from the baby unit until the noise stops; OR</li> <li>Turn down the volume of your parent unit.</li> </ul>
Why does the parent unit beep?	The baby unit may be out of range. Move the parent unit closer to the baby unit (but not less than 1 metre).
	The parent unit may not have enough charge for the parent unit to perform normally. Charge the battery in the parent unit until the battery icon becomes solid (
	The temperature of your baby's room may be too high or too low.
Why don't I hear a sound/Why can't I hear my baby cry?	The parent unit speaker volume may be too low. Press <b>VOL+</b> to increase the volume, or use the parent unit menu to change Sound Sensitivity level to a higher level.
Why can't I establish a connection? Why is the connection lost every now and then? Why are there sound interruptions?	The baby unit may be out of range. Move the parent unit closer to the baby unit (but not less than 1 metre).
	Other electronic products and wireless products may cause interference with your baby monitor. Try installing your baby monitor as far away from these devices as possible.

**DECLARATION OF CONFORMITY** 



# DISPOSAL OF BATTERIES AND PRODUCT

The crossed-out wheelie bin symbols on products and batteries, or on their respective packaging, indicates they must not be disposed of in domestic waste as they contain substances that can be damaging to the environment and human health.

The chemical symbols Hg, Cd or Pb, where marked, indicate that the battery contains more than the specified value of mercury (Hg), cadmium (Cd) or lead (Pn) set out in Battery Directive

The solid bar indicates that the product was placed on the market after 13th August, 2005.

The Background Noise sound file was created by Caroline Ford, and is used under the Creative Commons license. The *Stream Noise* sound file was created by Caroline Ford, and is used under the Creative Commons license. he Crickets At Night sound file was created by Mike Koenig, and is used under the Creative Commons license. The Heart Beat sound file was created by Zarabadeu, and is used under the Creative Commons license.

23/F., Tai Ping Industrial Centre, Block 1, 57 Ting kok Road, Tai Po, Hong Kong.

Napier Court, Abingdon Science Park, Abingdon, Oxon, OX14 3YT, U.K.